

204 Motor Carrier Load Tender - Transportation Version 004010

Functional Group=**SM**

Purpose:

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	ST	Transaction Set Header	M	1			Must use
020	B2	Beginning Segment for Shipment Information Transaction	M	1			Must use
030	B2A	Set Purpose	M	1			Must use
080	L11	Business Instructions and Reference Number	O	50			Used
090	G62	Date/Time	O	1		N1/090	Used
120	PLD	Pallet Information	O	1			Used
130	NTE	Note/Special Instruction	O	10			Used
LOOP ID - 0100					5	N1/140L	
140	N1	Name	O	1		N1/140	Used
150	N2	Additional Name Information	M	1			Used
160	N3	Address Information	O	2			Used
170	N4	Geographic Location	O	1			Used
190	G61	Contact	O	3			Used
LOOP ID - 0200					10		
200	N7	Equipment Details	O	1			Used

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - 0300					999		
010	S5	Stop Off Details	M	1			Must use
020	L11	Business Instructions and Reference Number	O	50			Used
030	G62	Date/Time	O	2		N2/030	Used
065	NTE	Note/Special Instruction	O	20			Used
LOOP ID - 0310					1		
070	N1	Name	O	1			Used
090	N3	Address Information	O	2			Used
100	N4	Geographic Location	O	1			Used
120	G61	Contact	O	3			Used
LOOP ID - 0350					999	N2/150L	
150	OID	Order Identification Detail	O	1		N2/150	Used

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	L3	Total Weight and Charges	O	1			Used
020	SE	Transaction Set Trailer	M	1			Must use

User:

The 990 Response to a Load Tender must be transmitted by the date and time specified in a G62 segment at the Header Level with a G6201 value of "64".

***** The 990 replaces the 997. Do not send a 997 in acknowledgement of the 204. *****

ST Transaction Set Header

Pos: 010	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use
ST02	329	Transaction Set Control Number	M	AN	4/9	Must use

B2 Beginning Segment for Shipment Information Transaction

Pos: 020	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 3

User Option (Usage): Must use

Purpose: To transmit basic data relating to shipment information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
B202	140	Standard Carrier Alpha Code	O	ID	2/4	Used
User: This element is required for the 990 and 214.						
B204	145	Shipment Identification Number	O	AN	1/30	Used
User: This element will contain the Master Bill of Lading.						
This value must be returned in the B102 element of the 990 and the B1002 element of the 214.						
B206	146	Shipment Method of Payment	M	ID	2/2	Must use
CodeList Summary (Total Codes: 28, Included: 2)						
Code Name						
CC Collect						
PP Prepaid (by Seller)						

B2A Set Purpose

Pos: 030	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 1

User Option (Usage): Must use

Purpose: To allow for positive identification of transaction set purpose

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
B2A01	353	Transaction Set Purpose Code	M	ID	2/2	Must use

User: A 990 must be returned since the 997 is not being used.

CodeList Summary (Total Codes: 65, Included: 4)

<u>Code</u>	<u>Name</u>
00	Original
01	Cancellation
04	Change
05	Replace

L11 Business Instructions and Reference Number

Pos: 080	Max: 50
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

Purpose: To specify instructions in this business relationship or a reference number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
L1101	127	Reference Identification	C	AN	1/30	Used

User: 2I - Tracking Number

This value must be returned in a Header Level N9 of the 990. This will allow the returned 990 to be linked to the correct parent 204 since more than one document(original + changes) may be transmitted per tender.

BM - Bill of Lading

This value must be returned in the V9 Segment of the 990 and a Header Level L11 in the 214. It will be 12 variable alpha/numeric characters and is different from the value sent in the B204. This links the 990's and 214's to another application.

The value is formatted as follows:

Positions 1 & 2 will always = 00

Positions 3 to 11 = variable BOL Number

Position 12 always = M if TL, S if LTL

Examples: (X = variable BOL)

TL = 00XXXXXXXXXXM

LTL = 00XXXXXXXXXXS

L1102	128	Reference Identification Qualifier	C	ID	2/3	Used
-------	-----	------------------------------------	---	----	-----	------

CodeList Summary (Total Codes: 1503, Included: 3)

Code Name

2I Tracking Number

BM Bill of Lading Number

CMN Continuous Move Number

User:

G62 Date/Time

Pos: 090	Max: 1
Heading - Optional	
Loop: N/A	Elements: 5

User Option (Usage): Used

Purpose: To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
G6201	432	Date Qualifier	C	ID	2/2	Used
CodeList Summary (Total Codes: 137, Included: 1)						
<u>Code</u> <u>Name</u>						
64 Must Respond By						
G6202	373	Date	C	DT	8/8	Used
G6203	176	Time Qualifier	C	ID	1/2	Used
CodeList Summary (Total Codes: 42, Included: 1)						
<u>Code</u> <u>Name</u>						
1 Must Respond By						
G6204	337	Time	C	TM	4/8	Used
G6205	623	Time Code	O	ID	2/2	Used

User: The Must Respond By date/time will be Eastern Time(ET).

CodeList Summary (Total Codes: 51, Included: 1)

Code Name

ET Eastern Time

User:

If G6201 = "64", then G6203 will = "1". Latest date/time for transmitting a 990. Load will be re-rendered after this date and time.

PLD Pallet Information

Pos: 120	Max: 1
Heading - Optional	
Loop: N/A	Elements: 1

User Option (Usage): Used

Purpose: To specify pallet information including quantity, exchange, and weight

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PLD01	406	Quantity of Pallets Shipped	M	NO	1/3	Must use

User:

This is the estimated value of pallet positions for this load, not an exact count of GMA pallets.

NTE Note/Special Instruction

Pos: 130	Max: 10
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

Purpose: To transmit information in a free-form format, if necessary, for comment or special instruction

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
NTE01	363	Note Reference Code	O	ID	3/3	Used

User: Loading dates/times will be transmitted within the NTE02. This is due to a standards restriction on the number of G62 segments allowed at the heading level.

CodeList Summary (Total Codes: 241, Included: 1)

Code Name

LOI Loading Instructions

NTE02	352	Description	M	AN	1/80	Must use
-------	-----	--------------------	---	----	------	----------

User: A maximum of two NTE segments will be transmitted. The data will be formatted as follows.

Positions	Data
1 to 3	Type of date - EPU(earliest pick-up)
1 to 3	LPU(latest pick-up)
1 to 3	SPU(scheduled pick-up)
4 to 4	Filler(blank)
5 to 5	-(dash)
6 to 6	Filler(blank)
7 to 14	Date(CCYYMMDD format)
15 to 16	Filler(blanks)
17 to 20	Associated Time(HHMM)

EPU and LPU are paired. Both will be sent.

SPU is stand alone and is designed for future use. It will currently not be sent, but should be planned for.

Examples:

EPU - 19990115 0700 Earliest Pick-up - Jan. 15, 1999 at 0700

LPU - 19990115 1900 Latest Pick-up - Jan. 15, 1999 at 1900

or

SPU - 19990115 1000 Sceduled Pick-up - Jan 15,1999 at 1000

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
------------	-----------	---------------------	------------	-------------	----------------	--------------

User:

The carrier is advised to call for an exact pickup date and time prior to arrival.
Once an exact pick-up date and time are obtained, this information is to be relayed back via the 214.
Contact information will be found in G61 segments within the N1 loop at the header level.
Pool distribution(other than Pool line haul) is excluded from pickup date/time scheduling.

N1 Name

Pos: 140	Max: 1
Heading - Optional	
Loop: 0100	Elements: 3

Loop Path: 0100

User Option (Usage): Used

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use
CodeList Summary (Total Codes: 1312, Included: 1)						
<u>Code</u> <u>Name</u>						
SF Ship From						
N103	66	Identification Code Qualifier	C	ID	1/2	Used
CodeList Summary (Total Codes: 215, Included: 1)						
<u>Code</u> <u>Name</u>						
91 Assigned by Seller or Seller's Agent						
N104	67	Identification Code	C	AN	2/80	Used
User: This is the Hershey facility number for pick-up.						

User:

If there is to be more than one pick-up, this will be the origination point. Additional pickup locations will be transmitted within the S5 loop at the Detail Level.
 When responding with either a 990 or 214, this should be considered stop number 1, unless the shipping point is a pool.

N2 Additional Name Information

Pos: 150	Max: 1
Heading - Mandatory	
Loop: 0100	Elements: 1

Loop Path: 0100

User Option (Usage): Used

Purpose: To specify additional names or those longer than 35 characters in length

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N201	93	Name	M	AN	1/60	Must use

N3 Address Information

Pos: 160	Max: 2
Heading - Optional	
Loop: 0100	Elements: 2

Loop Path: 0100

User Option (Usage): Used

Purpose: To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	M	AN	1/55	Must use
N302	166	Address Information	O	AN	1/55	Used

N4 Geographic Location

Pos: 170 Max: 1
 Heading - Optional
 Loop: 0100 Elements: 4

Loop Path: 0100

User Option (Usage): Used

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Used
N402	156	State or Province Code	O	ID	2/2	Used
N403	116	Postal Code	O	ID	3/15	Used
N404	26	Country Code	O	ID	2/3	Used

G61 Contact

Pos: 190	Max: 3
Heading - Optional	
Loop: 0100	Elements: 4

Loop Path: 0100

User Option (Usage): Used

Purpose: To identify a person or office to whom communications should be directed

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
G6101	366	Contact Function Code	M	ID	2/2	Must use
CodeList Summary (Total Codes: 230, Included: 1)						
<u>Code</u> <u>Name</u>						
SH Shipper Contact						
G6102	93	Name	M	AN	1/60	Must use
G6103	365	Communication Number Qualifier	C	ID	2/2	Used
CodeList Summary (Total Codes: 40, Included: 3)						
<u>Code</u> <u>Name</u>						
EM Electronic Mail						
FX Facsimile						
TE Telephone						
G6104	364	Communication Number	C	AN	1/80	Used

User:

The G61 segment can occur up to three times.
No G61 segments will be transmitted to a pool.

N7 Equipment Details

Pos: 200	Max: 1
Heading - Optional	
Loop: 0200	Elements: 3

Loop Path: 0200

User Option (Usage): Used

Purpose: To identify the equipment

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N702	207	Equipment Number	M	AN	1/10	Must use

User: This element is included because it is mandatory. A value of '1' will be transmitted.

N711	40	Equipment Description Code	O	ID	2/2	Used
------	----	-----------------------------------	---	----	-----	------

User: "CN" and "CZ" will denote ocean shipping containers.

"CN" is dry.

"CZ" is refrigerated.

CodeList Summary (Total Codes: 134, Included: 4)

Code Name

- CN Container
- CZ Refrigerated Container
- RT Controlled Temperature Trailer (Reefer)
- TF Trailer,Dry Freight

N715	567	Equipment Length	O	N0	4/5	Used
------	-----	-------------------------	---	----	-----	------

User: Length will be transmitted in feet and inches formatted as FFFII.

FFF is the feet and II is the inches. Inches will range from 00 to 11.

S5 Stop Off Details

Pos: 010	Max: 1
Detail - Mandatory	
Loop: 0300	Elements: 8

Loop Path: 0300

User Option (Usage): Must use

Purpose: To specify stop-off detail reference numbers and stop reason

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
S501	165	Stop Sequence Number	M	NO	1/3	Must use

User: For line haul, this will start at 2 and increment by 1 for each additional occurrence. The origin point as specified by the N1 at the Header Level is stop number 1.

If a pool, this value will always be 1.

S502	163	Stop Reason Code	M	ID	2/2	Must use
------	-----	------------------	---	----	-----	----------

User: A "PL" will only be used if there is more than one pick-up. It is assumed that the initial pick-up will occur at the origination point as specified in the N1 Loop at the Header Level.

CodeList Summary (Total Codes: 19, Included: 3)

Code Name

CU Complete Unload
 PL Part Load
 PU Part Unload

S503	81	Weight	C	R	1/10	Used
------	----	--------	---	---	------	------

S504	188	Weight Unit Code	C	ID	1/1	Used
------	-----	------------------	---	----	-----	------

CodeList Summary (Total Codes: 8, Included: 1)

Code Name

L Pounds

S505	382	Number of Units Shipped	C	R	1/10	Used
------	-----	-------------------------	---	---	------	------

S506	355	Unit or Basis for Measurement Code	C	ID	2/2	Used
------	-----	------------------------------------	---	----	-----	------

CodeList Summary (Total Codes: 794, Included: 1)

Code Name

PC Piece

S507	183	Volume	C	R	1/8	Used
------	-----	--------	---	---	-----	------

S508	184	Volume Unit Qualifier	C	ID	1/1	Used
------	-----	-----------------------	---	----	-----	------

User: Hershey's cubic feet calculation is based on an estimate of the "pallet position cubic feet" which results from the actual product mix of the shipment as a result of single stack requirements, etc.

CodeList Summary (Total Codes: 16, Included: 1)

Code Name

E Cubic Feet

L11 Business Instructions and Reference Number

Pos: 020	Max: 50
Detail - Optional	
Loop: 0300	Elements: 2

Loop Path: 0300

User Option (Usage): Used

Purpose: To specify instructions in this business relationship or a reference number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
L1101	127	Reference Identification	C	AN	1/30	Used

User: If L1102 = "VI", then L1101 will be the Pool BOL. It will only be sent if the stop is a pool.

L1102	128	Reference Identification Qualifier	C	ID	2/3	Used
-------	-----	------------------------------------	---	----	-----	------

User: Code VI will only be sent if the stop is a pool. L1101 will then contain the Pool BOL.

CodeList Summary (Total Codes: 1503, Included: 2)

Code Name

- AO Appointment Number
- VI Pool Number

User:

If a Pool BOL is transmitted, there will be no OID segments. Pool delivery information will be sent to the pools in separate 204's.

G62 Date/Time

Pos: 030	Max: 2
Detail - Optional	
Loop: 0300	Elements: 5

Loop Path: 0300

User Option (Usage): Used

Purpose: To specify pertinent dates and times

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
G6201	432	Date Qualifier	C	ID	2/2	Used

User: Note: Scheduled Pick-Up(Code 69) will currently not be transmitted. It is designated for future functionality, but plan for it.

CodeList Summary (Total Codes: 137, Included: 7)

Code Name

- 53 Deliver Not Before Date
- 54 Deliver No Later Than Date
- 68 Requested Delivery Date
- 69 Scheduled Pick-Up Date
- 70 Scheduled Delivery Date
- EP Earliest Pickup Date
- LP Latest Pickup Date

G6202	373	Date	C	DT	8/8	Used
G6203	176	Time Qualifier	C	ID	1/2	Used

CodeList Summary (Total Codes: 42, Included: 6)

Code Name

- U Scheduled Pick Up Time
- X Scheduled Delivery Time
- ED Earliest Delivery Time
- EP Earliest Pickup Time
- LD Latest Delivery Time
- LP Latest Pickup Time

G6204	337	Time	C	TM	4/8	Used
G6205	623	Time Code	O	ID	2/2	Used

User: All times will be relayed in the appropriate local time of the destination.

CodeList Summary (Total Codes: 51, Included: 1)

Code Name

- LT Local Time

User:

The following will only be transmitted if S502 is a "CU"(Complete Unload) or "PU"(Part Unload).

If G6201 = "53", then G6203 will = "ED"*

If G6201 = "54", then G6203 will = "LD"*

If G6201 = "70", then G6203 will = "X". This is a firm delivery appointment.

* If providing a delivery window, both of these segments will be sent. Carrier is to set the exact appointment date/time and relay that information to Hershey in a 214.

The following will be only be sent if S502 is equal to "PL"(Part Load).

If G6201 = "69", then G6203 will = "U". This is a firm pickup appointment.

If G6201 = "EP", then G6203 will = "EP"***

If G6201 = "LP", then G6203 will = "LP"***

** If providing a pick-up window, both segments will be sent. The carrier is advised to call for an exact pickup date and time prior to arriving. Contact information is sent in a G61 segment within a Detail Level N1 loop. Pool distribution (other than Pool line haul) is excluded from pickup date/time scheduling.

Note: Once an exact pick-up or delivery date/time is obtained, this information must be sent back in a 214.

NTE Note/Special Instruction

Pos: 065	Max: 20
Detail - Optional	
Loop: 0300	Elements: 2

Loop Path: 0300

User Option (Usage): Used

Purpose: To transmit information in a free-form format, if necessary, for comment or special instruction

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
NTE01	363	Note Reference Code	O	ID	3/3	Used
CodeList Summary (Total Codes: 241, Included: 1)						
		<u>Code</u> <u>Name</u>				
		DEL Delivery				
NTE02	352	Description	M	AN	1/80	Must use

User:

This segment will contain information about the delivery.

N1 Name

Pos: 070	Max: 1
Detail - Optional	
Loop: 0310	Elements: 4

Loop Path: 0300-0310

User Option (Usage): Used

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use
CodeList Summary (Total Codes: 1312, Included: 3)						
<u>Code</u> <u>Name</u>						
CN Consignee						
CS Consolidator						
PW Pick Up Address						
N102	93	Name	C	AN	1/60	Used
N103	66	Identification Code Qualifier	C	ID	1/2	Used
CodeList Summary (Total Codes: 215, Included: 1)						
<u>Code</u> <u>Name</u>						
91 Assigned by Seller or Seller's Agent						
N104	67	Identification Code	C	AN	2/80	Used

User:

N101 will = "CS" if the stop is a pool distribution location. The N104 will denote the Hershey Account Number for the pool distribution location.
 If N101 = "PW", then N104 will contain the Hershey Facility Number. Please see Appendix A for this 4 digit value.
 The N3 and N4 segments will not be sent.
 N103 and N104 will not be transmitted if N101 = "CN"

N3 Address Information

Pos: 090	Max: 2
Detail - Optional	
Loop: 0310	Elements: 2

Loop Path: 0300-0310

User Option (Usage): Used

Purpose: To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	M	AN	1/55	Must use
N302	166	Address Information	O	AN	1/55	Used

N4 Geographic Location

Pos: 100	Max: 1
Detail - Optional	
Loop: 0310	Elements: 4

Loop Path: 0300-0310

User Option (Usage): Used

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Used
N402	156	State or Province Code	O	ID	2/2	Used
N403	116	Postal Code	O	ID	3/15	Used
N404	26	Country Code	O	ID	2/3	Used

User:

A value will only be sent if it is other than "USA".

G61 Contact

Pos: 120	Max: 3
Detail - Optional	
Loop: 0310	Elements: 4

Loop Path: 0300-0310

User Option (Usage): Used

Purpose: To identify a person or office to whom communications should be directed

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
G6101	366	Contact Function Code	M	ID	2/2	Must use

User: "DC" denotes(if available) the person to be contacted to schedule the delivery.

"SH" denotes the Hershey contact person if this a pickup.

CodeList Summary (Total Codes: 230, Included: 2)

<u>Code</u>	<u>Name</u>
DC	Delivery Contact
SH	Shipper Contact

G6102	93	Name	M	AN	1/60	Must use
G6103	365	Communication Number Qualifier	C	ID	2/2	Used

CodeList Summary (Total Codes: 40, Included: 2)

<u>Code</u>	<u>Name</u>
FX	Facsimile
TE	Telephone

G6104	364	Communication Number	C	AN	1/80	Used
-------	-----	----------------------	---	----	------	------

User:

The G61 segment can occur up to two times.

OID Order Identification Detail

Pos: 150	Max: 1
Detail - Optional	
Loop: 0350	Elements: 9

Loop Path: 0300-0350

User Option (Usage): Used

Purpose: To specify order identification detail

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
OID01	127	Reference Identification	C	AN	1/30	Used
		User: This will contain the Stop BOL. If there is more than one order for the stop, this value will be the same for all OID segments.				
OID02	324	Purchase Order Number	C	AN	1/22	Used
OID03	127	Reference Identification	O	AN	1/30	Used
		User: This value will be the Order BOL.				
OID04	355	Unit or Basis for Measurement Code	C	ID	2/2	Used
		CodeList Summary (Total Codes: 794, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		PC	Piece			
OID05	380	Quantity	C	R	1/15	Used
OID06	188	Weight Unit Code	C	ID	1/1	Used
		CodeList Summary (Total Codes: 8, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		L	Pounds			
OID07	81	Weight	C	R	1/10	Used
OID08	184	Volume Unit Qualifier	C	ID	1/1	Used
		User: Please see S508 for Hershey's definition of cubic feet.				
		CodeList Summary (Total Codes: 16, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		E	Cubic Feet			
OID09	183	Volume	C	R	1/8	Used

User:

OID segments will not be transmitted if the delivery location is a pool.

L3 Total Weight and Charges

Pos: 010 Max: 1
 Summary - Optional
 Loop: N/A Elements: 5

User Option (Usage): Used

Purpose: To specify the total shipment in terms of weight, volume, rates, charges, advances, and prepaid amounts applicable to one or more line items

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
L301	81	Weight	C	R	1/10	Used
L302	187	Weight Qualifier	C	ID	1/2	Used
CodeList Summary (Total Codes: 51, Included: 1)						
<u>Code</u> <u>Name</u>						
G Gross Weight						
L309	183	Volume	C	R	1/8	Used
L310	184	Volume Unit Qualifier	C	ID	1/1	Used
User: Please see S508 for Hershey's definition of cubic feet.						
CodeList Summary (Total Codes: 16, Included: 1)						
<u>Code</u> <u>Name</u>						
E Cubic Feet						
L311	80	Lading Quantity	O	N0	1/7	Used

User:

The value in L311 is expressed in pieces.

SE Transaction Set Trailer

Pos: 020	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	N0	1/10	Must use
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use